









**Motion detector top unit 1.10 m Standard for KNX  
System 55**



| Specification   | Order No. | Packing unit | PS | EAN           |
|---|-----------|--------------|----|---------------|
|  cream white glossy           | 2040 01   | 1/5          | 06 | 4010337026808 |
|  pure white glossy           | 2040 03   | 1/5          | 06 | 4010337026815 |
|  pure white matt             | 2040 27   | 1/5          | 06 | 4010337026822 |
|  anthracite                  | 2040 28   | 1/5          | 06 | 4010337026839 |
|  colour aluminium            | 2040 26   | 1/5          | 06 | 4010337026846 |
|  black matt                  | 2040 005  | 1/5          | 06 | 4010337037217 |
|  grey matt                   | 2040 015  | 1/5          | 06 | 4010337082965 |
|  stainless steel (lacquered) | 2040 600  | 1/5          | 06 | 4010337033059 |

## Features

- Installation on bus coupler 3.
- Configurable for motion detection (sentinel application) or for room monitoring (detector application).
- Evaluation of brightness during active motion detection in sentinel mode. Switching off lights when brightness threshold is exceeded.
- Configurable number of motion impulses within one monitoring time in detection mode.
- Digital motion detection via 2 PIR sensors.
- Sensitivity of motion detection can be parameterised separately in steps for the PIR sectors.
- Integrated brightness sensor for determining ambient brightness.
- Adjustment of sensitivity via a dial on the device.
- Indication of motion detection (permanent or only during walking test).
- One function block can be configured.
- Function block for the "sentinel", "sentinel with switch-off brightness" or "detector" application configurable.
- Two output communication objects are available to the function block which are transmitted to the KNX via the switching and control commands.
- Configurable functions: switching, staircase function, dimming value transmitter, scene auxiliary unit, temperature value transmitter, brightness value transmitter, operating mode changeover, switching with forced setting.
- Switchover of the operating mode (OFF / AUTO / ON) during ongoing operation through local operation or via communication object through local operation at other motion detectors for KNX using pushbutton sensor for KNX or visualisation.
- In brightness-independent operation, the function block can determine the time span after a previous movement and transmit it to the KNX via a communication object. This function allows for simple monitoring of movements, for example of persons in assisted living residences or in a retirement home.
- Functionality of motion detection adjustable for the "sentinel" or "sentinel with switch-off brightness" application.
- For the "sentinel" or "sentinel with switch-off brightness" applications, the device can be used as a single device, main unit or auxiliary unit.
- Walking test function to help in planning and adjusting the PIR detection range.

---

## Technical data

|                                |                      |
|--------------------------------|----------------------|
| KNX medium:                    | TP256                |
| Mounting height up to 1.10 m   |                      |
| - Range of detection forwards: | Max. 32 m            |
| - Range to each side:          | Max. 19 m            |
| Angle of detection:            | 180°                 |
| Brightness sensor              |                      |
| - Measurement range:           | approx. 1 to 1000 lx |
| Protection class               |                      |
| - System 55, Gira F100:        | IP20                 |
| - TX_44:                       | IP44                 |
| Ambient temperature:           | -5 °C to +45 °C      |

---

## Notes

- Suitable for indoor use only.
- The motion detector is not suitable for alarm messages in VdS-compliant alarm systems.