GIRA Data sheet

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Motion detector Cube 120



Specification		Order No.	Packing unit	£/piece without VAT	PS	EAN
	pure white glossy	2442 02	1	111.94	08	4010337056430
	anthracite	2442 10	1	117.04	08	4010337056416

Features

- Automatically switches lighting on/off, depending on thermal motion and ambient brightness.

- Automatic temperature-compensated sensor sensitivity.
- Continuous light (max. 2 h) can be activated using an optional switch/button.
- Test mode for evaluating the detection range.
- Individual adaptation of the detection range using the enclosed covering panel that can be cut to size.
- Adjustable switch-off delay: 5 s to 15 min or short-term operation of 1 s.
- Save current twilight value using teach-in function.
- Glare protection, brightness-independent sensor evaluation for 60 s in the event of glare caused by extraneous light.
- Short-time operation, output is switched on for approx. 1 s.
- Remote control optional.

Technical data

Rated voltage:	AC 230V~, 50/60Hz
Connected load - HV LED lamps: - Light bulbs: - Fluorescent lamps, uncompensated: - Fluorescent lamps, parallel-compensated: - Fluorescent lamps, series-compensated:	typically 200 W 2000 W 1000 VA (cos φ = 0.5) 500 W (45.6 μF) 900 W
Capacitive load:	176 µF
Brightness value - Brightness value:	2 to 1000 lx
Setting controller - Delay time:	5 seconds to 15 minutes

catalogue.gira.com

GIRA Data sheet

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Connection cross section - Single-wire: - Fine-wire without core jacket: - fine-wire with core jacket:	Max. 2.5 mm² Max. 2.5 mm² Max. 1.5 mm²
Protection level:	IP54
Ambient temperature:	-25 °C to +55 °C
Angle of detection:	120°
Mounting height 2.50 m - Detection range facing forwards, max.: - Range at each side, max.:	approx. 16 m approx. 11 m

Notes

- Suitable for ceiling and wall mounting indoors and outdoors.

- Optional: Can be controlled remotely using IR remote control PIR 3.

- Observe high peak switch-on currents with "energy saving lamps". Check suitability of the lamps before use!

Scope of supply

- Covering panel for adapting the detection range is included in the scope of supply.