


**System 3000 operating top unit BT arrow symbols**  
**System 55**



| Specification   | Order No. | Packing unit | £/piece<br>without VAT | PS | EAN           |
|---|-----------|--------------|------------------------|----|---------------|
|  cream white glossy | 5382 01   | 1/5          | 116.20                 | 02 | 4010337122524 |
|  pure white glossy | 5382 03   | 1/5          | 116.20                 | 02 | 4010337122531 |
|  pure white matt   | 5382 27   | 1/5          | 116.20                 | 02 | 4010337122593 |
|  anthracite        | 5382 28   | 1/5          | 118.82                 | 02 | 4010337122609 |
|  colour aluminium  | 5382 26   | 1/5          | 122.90                 | 02 | 4010337122579 |
|  black matt        | 5382 005  | 1/5          | 122.90                 | 02 | 4010337122616 |
|  grey matt         | 5382 015  | 1/5          | 122.90                 | 02 | 4010337122623 |
|  stainless steel   | 5382 600  | 1/5          | 130.35                 | 02 | 4010337122630 |

## Features

- Operation with System 3000 blind control insert.
- Operating blinds, shutters and awnings.
- An individual intermediate position can be saved with the blind control insert.
- Can also be used for light applications.
- Operation and programming with mobile end device (smartphone or tablet) via Bluetooth® using the Gira System 3000 App.
- Operation on System 3000 switching, dimming or blind insert and 3-wire auxiliary unit.

### Functions on the top unit

- Operation of hangings and lighting.
- The runtime and an individual intermediate position can be saved using the System 3000 blind controller insert.
- Switch-on brightness of lighting can be saved using System 3000 dimming insert or DALI Power control unit.

### Functions with the Gira System 3000 app

- Operation of hangings and lighting with status feedback.
- Display the current hanging position or dimmer setting.
- Activate/deactivate automatic mode.
- Adjustable night mode. Status LED and function LED are not lit up continuously.
- Programming of up to 40 individual switching times.
- Blind or slat positions or switching and dimming values can be stored for each switching time.
- Switching times can be copied to other devices.
- Switching at sunrise or sunset (astro function).
- Astro time can be optimised by determining the location.
- Astro time shift adjustable.
- Random function.
- Automatic date and time refresh when connecting smartphones or tablets.
- Password protection possible for time programs and configuration.
- Save a curtain position, curtain runtime, slat reversal time.
- Changeover to inverse operation possible for blind inserts.
- Maximum brightness and minimum brightness adjustable for dimming insert.

---

## Technical data

|                      |                      |
|----------------------|----------------------|
| Ambient temperature: | -5 °C to +45 °C      |
| Accuracy             |                      |
| - Per month:         | ± 10 s               |
| Power reserve:       | approx. 4 h          |
| Wireless frequency:  | 2.402 to 2.480 GHz   |
| Transmission power:  | max. 2.5 mW, class 2 |
| Transmission range:  | typically 10 m       |
| Ambient temperature: | -5 °C to +45 °C      |

---

## Notes

- The time is updated upon connection to the Gira System 3000 app.