© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

## Antenna socket insert (SE33ST)

**GIRA** Data sheet



Specification	Order No.	Packing unit	PS	EAN
	0937 00	1/5	01	4010337937005

## **Features**

- Stub cable outlet with three connections.
- The IEC plug for terrestrial TV is located on the bottom left, the IEC socket for FM (radio) on the bottom right and at the top centre is the F connector for satellite TV (SAT).
- Channel filter for terrestrial and satellite television with high attenuation rate: The SAT signal is filtered in the FM-TV-IEC connections, while the terrestrial FM/TV signal is filtered in the satellite F connection.
- DC feed-through from the SAT connection to the input.
- The internal conductor is connected simply by pressing it, without the need for screws. Internal conductor can thus be removed multiple
- Complies with shield class A.

## Technical data

UKW frequency band

87.5 to 108 MHz - Frequency range: - Decoupling: > 10 dB

UKW frequency band: 4 dB

TV frequency band

- Frequency range: 125 to 862 MHz - Decoupling: > 10 dB - Attenuation: TV plug: 4 dB

SAT frequency band

950 to 2400 MHz - Frequency range: - Decoupling: > 20 dB - Attenuation: SAT plug: 1.5 dB

36 mm Installation depth:

## **GIRA** Data sheet

catalogue.gira.com

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

- For screw attachment only.