



Gira G1 230 V



Specification	Order No.	Packing unit	PS	EAN
 black glass	2067 05	1	36	4010337014294
 white glass	2067 12	1	36	4010337014324

The Gira G1 is a multi-functional room operating device for visualising and operating a variety of building functions. For use in the KNX system and Gira door communication system.

Features

- Operation is via a gesture-capable multi-touch display.
- Connection and communication are via LAN or WLAN depending on the version.
- Integrated speaker.
- Integrated microphone with echo compensation.

Properties as a KNX room operating device

- Intuitive user interface that can be adapted by the end user.
- Switching, dimming, blind and shutter control, value transmitter, scene auxiliary unit.
- Status display, display of date and time, display of indoor and outdoor temperature.
- Up to 125 functions (five function folders or rooms with up to 25 functions each).
- Up to 125 seven-day timer with 10 switching times each.

Properties as a KNX room temperature controller

- Use as room temperature controller in combination with KNX devices for room temperature measurement, e.g. touch sensor 3 Komfort.
- Use as room temperature controller auxiliary unit in combination with KNX 3 Plus pushbutton sensor for room temperature measurement and control.
- Operating modes: Comfort, standby, night, and frost or heat protection with their own temperature setpoint values (for heating and/or cooling).
- Operating modes can be adapted individually.
- Comfort extension using the presence button.

- Frost or heat protection changeover using window status.
- Display of room temperature controller information.
- Control parameters for PI controllers and 2-point controllers can be set.
- A heating clock as seven-day timer with 28 switching times.

Properties as video home station

- Camera changeover: specific selection of connected colour cameras.
- Control of the door opener.
- Switching the ringtone on and off.
- Ring tone can be selected from a choice of 10 melodies.
- Call acceptance.
- Adjustment of ring tone and voice volume.

Integration of Internet services

- Gira weather service: display of the weather forecast for up to five cities (internet connection required).
- Gira G1 with flush-mounted connection module 230 V WLAN.
- Data communication via WLAN.

Technical data

Power consumption

- Maximum: 7 W
- Typical: 4 W
- Minimum: 2 W

Display

- Type: TFT
- Size: 15.3 cm (6")
- Number of colours: 16.7 M
- Resolution: 480 x 800 px (WVGA), 155 ppi
- Brightness: 350 cd/m²
- Contrast ratio: 1:500
- Viewing angle: > 80° all around

Proximity sensor

- Range: max. 50 cm
- Detection range: 30° horizontal, 30° vertical

KNX medium:

KNXnet/IP

KNX standards

- DPTs value transmitter: 5.010, 6.010, 5.001, 5.004, 9.001

Protection type:

IP21

Ambient temperature:

0 °C to +45 °C

Power supply:

AC 230 V, 50/60 Hz

WLAN standard:

IEEE 802.11b/g/n - 2.4 GHz

Installation depth:

32 mm

Notes

- Suitable for indoor use only.

- Recommended mounting height: 150 cm above floor.
- Installation is performed on a deep device box (an electronics box is recommended for a LAN connection).
- Communication with the KNX installation is exclusively via the KNXnet/IP standard.
- A KNX IP router must be used to connect the Gira G1 PoE to the KNX installation. Several Gira G1 units can be operated on one KNX IP router.
- In order to ensure reliable communication via WLAN, a Gira KNX IP router (firmware version 3 and later) is required to connect the Gira G1 230 V or G1 24 V to the KNX installation. For this purpose the Gira KNX IP router (firmware version 3 and later) is specially equipped with the additional function "Reliable data communication". Several Gira G1 units can be operated on one Gira KNX IP router (firmware version 3 and later).
- Start-up in the KNX system from ETS 4.2 or higher.
- Can be used as a home station in connection with the DCS-IP gateway.
- When planning the system, please observe the technical information on network planning in the device documentation.
- The Gira Project Assistant (GPA) is required for firmware updates. The GPA is available free of charge in the Gira download area.
- Using the timers requires either an internet connection to a NTP time server or a KNX clock (e.g. Gira weather station Plus 2074 00).

Scope of supply

- Display module, holding frame, flush-mounted connection module 230 V WLAN

Dimensions in mm

Gira G1 (incl. flush-mounted power supply unit):	97	168	47
Gira G1 (without flush-mounted power supply unit):	97	168	15
Mounting height:	-	1500	-
