www.gira.com

RCCB 30 mA



GIRA Data sheet

| Specification | | Order No. | Packing unit | PS | EAN |
|---------------|--------------------|-----------|--------------|----|---------------|
| | cream white glossy | 2664 01 | 1 | 03 | 4010337011897 |
| | pure white glossy | 2664 03 | 1 | 03 | 4010337011903 |
| | pure white matt | 2664 27 | 1 | 03 | 4010337011910 |
| | anthracite | 2664 28 | 1 | 03 | 4010337011927 |
| | colour aluminium | 2664 26 | 1 | 03 | 4010337011934 |
| | black matt | 2664 005 | 1 | 03 | 4010337037064 |
| | grey matt | 2664 015 | 1 | 03 | 4010337085232 |

Features

- The RCD is a permanently installed protective device with voltage-dependent residual current tripping in accordance with VDE0664. This device works like an RCD switch.

GIRA Data sheet

catalogue.gira.com

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Technical data

Rated voltage: AC 230 V, 50/60 Hz

Rated current: 16 A

Rated residual current: 30 mA

Installation depth: 32 mm

Connection cross section

- for conductors from: 1.5 mm² to 2.5 mm²

Ambient temperature: -25 °C to +40 °C

Notes

- Areas of application: Parapet trunking, in front of socket outlets or in Gira energy profile.
- Mounting in a deep device box.