


Emergency set including Gira E2 cover frame



Specification	Order No.	Packing unit	£/piece without VAT	PS	EAN
 pure white glossy	0495 88	1	294.08	34	4010337495888

Features

- Call module with red LED signal light, integrated zero-voltage contact, optionally switchable buzzer (continuous tone) and the option of setting a flashing light or continuous light.
- Pull-cord button with 2.5 m long pull cord with red handle and reassurance light in the button housing, suitable for wall and ceiling mounting.
- Switch-off button with green switch-off key.
- Flush-mounted power supply unit 250 mA.
- The call set can be optionally upgraded with a duty room unit with an integrated sound generator for acoustic call signalling, green presence button with presence light, and yellow buzzer switch-off button.

Technical data

Power supply	
- Input voltage:	AC 100 to 240 V, 50 to 60 Hz
- Input current:	180 mA
- Output voltage:	DC 24 V
- Output current:	250 mA
Ambient temperature:	+ 5 °C to + 40 °C
Length of pull cord:	2.5 m
Installation:	Device boxes

Notes

- For installation in accordance with DIN VDE 0834, use an uninterruptible power supply.
- The components for upgrading the emergency set can be purchased individually.