© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Antenna socket insert (UD2415ST)

GIRA Data sheet



Specification	Order No.	Packing unit	PS	EAN
<u> </u>	0042 00	1/5	01	4010337042006

Features

- 2-gang routing box in plug-in technology.
- IEC plug for FM (radio) and DVB-T/T2.
- IEC pin jack for DVB-S/S2 (SAT).
- DC feed-through from the SAT connection to the input and bidirectional circulation between input and output with bridging of the DC voltage.
- The internal conductor is connected simply by pressing it, without the need for screws. Internal conductor can thus be removed multiple times.
- Complies with shield class A.

Technical data

TV frequency band

Frequency range: 5 to 862 MHz
Decoupling: > 40 dB
Transmission loss: 1.2 dB
Attenuation: R/TV plug: 13 dB

SAT frequency band

- Frequency range: 950 to 2400 MHz

Decoupling: > 35 dB
Transmission loss: 2 dB
Attenuation: SAT plug: 14 dB
Installation depth: 27 mm

Notes

- Suitable for terrestrial reception, area couplers, and satellite reception systems.
- For screw attachment only.