


Rain monitor



| Specification | Order No. | Packing unit | PS | EAN |
|---|-----------|--------------|----|---------------|
|  | 0586 00 | 1 | 06 | 4010337586005 |

Features

- The rain monitor with frost protection down to -20 °C and snow detection is used for the detection of rain, snow, and frost to protect awnings, winter gardens, roof ventilation elements, etc.
- The detection of the amount of precipitation can be set using a 2-pole DIP switch in the power supply unit of the rain sensor.

Technical data

Operating voltage

- Power supply unit: AC 230 V, 50 Hz
- Rain sensor: 12 to DC 24 V

Power consumption: Approx. 4.5 VA

Relay contact: 5 A at 250 V/50 Hz, zero-voltage

Protection type

- Power supply unit: IP40
- Rain sensor: IP 65

Connection

- Rain sensor/power supply unit: 6 x 0.5 mm², DC 12 to 24 V
- Power supply unit/binary input: 2 x 0.5 mm², AC 230 V
- Power supply unit: 3 x 1.5 mm², AC 230 V

Rain sensor/power supply unit cable length: max. 150 m

Scope of supply

- The connection cables are not included in the scope of supply.