


DALI potentiometer



| Specification | Order No. | Packing unit | PS | EAN |
|---|-----------|--------------|----|---------------|
|  | 2018 00 | 1 | 02 | 4010337023449 |

Features

- For switching on/off and adjusting brightness for lights with a DALI interface
- To create the DALI voltage, a DALI power supply or a DALI potentiometer with integrated power supply unit is required which confirm to the DALI specification (DIN IEC 60926).
- Can be operated simultaneously from several operating points. Communication is via Broadcast.
- A basic brightness or a switch-on brightness can be stored.

Technical data

| | |
|-------------------------|------------------------|
| Current consumption: | Max. 2 mA |
| Installation depth: | 32 mm |
| Single-wire connection: | Max. 4 mm ² |
| Ambient temperature: | -5 °C to +45 °C |

Notes

- When selecting the DALI power supply, the number of DALI devices and the DALI potentiometer (always counts as 1 device) must be considered.