

## Motion detector 1.10 m for Gira One



Specification	Order No.	Packing unit	PS	EAN
 pure white glossy	2038 03	1	06	4010337125525
 pure white matt	2038 27	1	06	4010337125532
 anthracite	2038 28	1	06	4010337125600
 black matt	2038 005	1	06	4010337125624
 grey matt	2038 015	1	06	4010337125631

### Features

- Motion detector (with passive infrared sensor/PIR) for Gira One.
- For automatic switching of Gira One actuators depending on movement and brightness.
- The delay time of the Gira One consumer is configured via the relevant actuator channel in the Gira Project Assistant (GPA).
- Integrated temperature sensor for measuring the room temperature.
- Integrated local button to control the Gira One consumer: Switching, staircase and scene.
- Commissioning the motion detector with the Gira Project Assistant (GPA) version 5.2.
- Encrypted data transfer between the Gira One devices.

### Features of the motion detector

- Large detection range (up to 238 m<sup>2</sup>).
- Expansion of the detection range with additional motion detectors.
- It is possible to limit the detection range.

- It is possible to configure the sensitivity of the sensors.
- Walking test function to help in planning and adjusting the PIR detection range.
- Mixed light measurement suitable for fluorescent lamps (FL/PL/ESL), halogen/light bulbs and LEDs.

#### Room temperature

- Temperature adjustment for the integrated temperature sensor.

#### LED display

- Status LED function selection: always OFF, movement display.

---

#### Notes

- Can be updated via the Gira Project Assistant (GPA).
  - The motion detector is not suitable for alarm messages in VdS-compliant alarm systems.
  - KNX Data Secure compatible.
  - Can be updated via the Gira Project Assistant (GPA).
-