





Motion detector 1.10 m for Gira One



| Specification | Order No. | Packing unit | PS | EAN |
|---|-----------|--------------|----|---------------|
|  pure white glossy | 2038 03 | 1 | 06 | 4010337125525 |
|  pure white matt | 2038 27 | 1 | 06 | 4010337125532 |
|  anthracite | 2038 28 | 1 | 06 | 4010337125600 |
|  black matt | 2038 005 | 1 | 06 | 4010337125624 |
|  grey matt | 2038 015 | 1 | 06 | 4010337125631 |

Features

- Motion detector (with passive infrared sensor/PIR) for Gira One.
- For automatic switching of Gira One actuators depending on movement and brightness.
- The delay time of the Gira One consumer is configured via the relevant actuator channel in the Gira Project Assistant (GPA).
- Integrated temperature sensor for measuring the room temperature.
- Integrated local button to control the Gira One consumer: Switching, staircase and scene.
- Commissioning the motion detector with the Gira Project Assistant (GPA) version 5.2.
- Encrypted data transfer between the Gira One devices.

Features of the motion detector

- Large detection range (up to 238 m²).
- Expansion of the detection range with additional motion detectors.
- It is possible to limit the detection range.

- It is possible to configure the sensitivity of the sensors.
- Walking test function to help in planning and adjusting the PIR detection range.
- Mixed light measurement suitable for fluorescent lamps (FL/PL/ESL), halogen/light bulbs and LEDs.

Room temperature

- Temperature adjustment for the integrated temperature sensor.

LED display

- Status LED function selection: always OFF, movement display.
-

Notes

- Can be updated via the Gira Project Assistant (GPA).
 - The motion detector is not suitable for alarm messages in VdS-compliant alarm systems.
 - KNX Data Secure compatible.
 - Can be updated via the Gira Project Assistant (GPA).
-