


KNX pushbutton sensor 3 Basis, 1-gang System 55



Specification	Order No.	Packing unit	PS	EAN
 Start-up rocker	5111 00	1/5	06	4010337086802

Features

- Mounting on bus coupler 3.
- Disassembly safeguard by screw connection.
- Rocker function: Switching, dimming, blind, value transmitter 1-byte, and scene auxiliary unit.
- White operating LED.
- Two red status LEDs per operating surface.
- Inscription space illumination for rocker sets with inscription space.
- Function of inscription space illumination and status LED can be configured.

Technical data

Ambient temperature:	-5 °C to +45 °C
Protection class:	III

Notes

- Professional labelling with the Gira Inscription Service www.marking.gira.com.
- The pushbutton sensor is supplied with a program-neutral start-up rocker. The suitable rocker set for the design line must be ordered separately.

Scope of supply

- Blank inscription labels included.
- Blank inscription labels included.