GIRA Data sheet

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

System 3000 impulse insert



Specification	Order No.	Packing unit	PS	EAN
	5410 00	1/5	02	4010337048305

Features

The staircase lighting mechanism is switched on manually or automatically.
Manual switching with System 3000 operating top unit.

- Automatic switching with motion detector top unit or presence and motion detector 360° top unit Bluetooth® from System 3000.

Technical data

Rated voltage:	AC 230 V, 50 Hz	
Standby:	0.25 to 0.45 W	
Current consumption:	approx. 2.8 mA	
Installation depth:	24 mm	
Installation:	in device box in accordance with DIN 49073	
Ambient temperature:	-5 °C to +45 °C	