© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

## Add-on module for built-in speaker

**GIRA** Data sheet



Specification	Order No.	Packing unit	£/piece without VAT	PS	EAN
	1259 00	1	101.87	18	4010337259008

### **Features**

- Up to twelve mechanical bell buttons can be connected.
- Additional bell buttons can be connected via additional add-on modules.
- Up to eleven add-on modules can be connected to one built-in speaker.
- Alternating current polling of the bell button connections to prevent oxidation on the button contacts.
- Compact size.
- Securing of connection terminals against incorrect connection.
- Attachment of the add-on module with screws or gluing.

### **Technical data**

Connections

Mech. Bell button:
Common earth of bell buttons:
Connection cable:
12 x screw terminal
1 x screw terminal
2 x connector strip

Protection class: IP44

Ambient temperature: -25 °C to +70 °C

Dimensions

- incl. fixing lug: W 67 x H 66.4 x D 27 mm - without fixing lug: W 67 x H 56 x D 27 mm

### Notes

- Module for extension of the built-in speaker when more than eight mechanical bell buttons are to be connected.
- This component enables door communication systems with up to 140 audio devices to be set up (e.g. 1 x built-in speaker, 11 x add-on modules for built-in speakers, 136 x surface-mounted home stations).
- Protection type IP44 only in combination with a suitable front or when installed.

# **GIRA** Data sheet

catalogue.gira.com

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

	Sco	ре	of	su	p	р	ly
--	-----	----	----	----	---	---	----

- The mounting materials are included with delivery.