


Emergency set System 55



| Specification | Order No. | Packing unit | £/piece without VAT | PS | EAN |
|--|-----------|--------------|------------------------|----|---------------|
|  pure white glossy | 2914 03 | 1 | 277.26 | 34 | 4010337067900 |

Features

- Call module with red LED signal light, integrated zero-voltage contact, optionally switchable buzzer (continuous tone) and the option of setting a flashing light or continuous light.
- Pull-cord button with 2.5 m long pull cord with red handle and reassurance light in the button housing, suitable for wall and ceiling mounting.
- Switch-off button with green switch-off key.
- Flush-mounted power supply unit 250 mA.
- The call set can be optionally upgraded with a duty room unit with an integrated sound generator for acoustic call signalling, green presence button with presence light, and yellow buzzer switch-off button.

Technical data

| | |
|----------------------|------------------------------|
| Power supply | |
| - Input voltage: | AC 100 to 240 V, 50 to 60 Hz |
| - Input current: | 180 mA |
| - Output voltage: | DC 24 V |
| - Output current: | 250 mA |
| Ambient temperature: | + 5 °C to + 40 °C |
| Length of pull cord: | 2.5 m |
| Installation: | Device boxes |

Notes

- For installation in accordance with DIN VDE 0834, use an uninterruptible power supply.
- The components for upgrading the emergency set can be purchased individually.