catalogue.gira.com

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Rocker indicator switch insert 10 AX 250 V~ with orange LED lighting element 230 V~ series switch

GIRA Data sheet



| Specification | Order No. | Packing unit | £/piece without VAT | PS | EAN |
|------------------------|-----------|--------------|------------------------|----|---------------|
| with mounting claws | 3115 00 | 10 | 27.90 | 01 | 4010337064473 |
| without mounting claws | 3825 00 | 1 | 27.90 | 01 | 4010337038900 |

Technical data

Installation depth

- 3115 00:

32 mm - 3825 00: 23 mm

Connection cross section

2.5 mm² - For rigid and flexible conductors up to:

Rated output

- LEDi/CFLi: 100 W

Scope of supply

- Orange LED lighting element 230 V~ 0.5 mA is included in the scope of supply.