


Pushbutton sensor 3 Basis, 2-gang (1+1) for KNX with start-up rocker



Specification	Order No.	Packing unit	£/piece without VAT	PS	EAN
	5112 00	1	102.83	06	4010337086819

Features

- Installation on bus coupler 3.
- Safeguarded from disassembly because it is screw-fastened.
- Rocker function: Switching, dimming, blind, value transmitter 1-byte, and scene auxiliary unit.
- White operating LED.
- Two red status LEDs per operating surface.
- Inscription space illumination for rocker sets with inscription space.
- Function of inscription space illumination and status LED can be configured.

Technical data

Ambient temperature:	-5 °C to +45 °C
Protection class:	III

Notes

- Professional inscription by the Gira inscription service www.marking.gira.com.
- The pushbutton sensor is delivered with a program-neutral start-up rocker. The suitable rocker set for the switch range must be ordered separately.

Scope of supply

- Plain inscription labels included.