GIRA Data sheet

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

System 3000 impulse insert



Specification	Order No.	Packing unit	PS	EAN
	5410 00	1	02	4010337048305

Features

- The staircase lighting mechanism is switched on manually or automatically.
- Manual switching with System 3000 operating top unit.
- Automatic switching with motion detector top unit or presence and motion detector 360° top unit Bluetooth® from System 3000.

Technical data

Rated voltage: AC 230 V, 50 Hz

Standby: 0.25 to 0.45 W

Current consumption: approx. 2.8 mA

Installation depth: 24 mm

Installation: in device box in accordance with DIN 49073

Ambient temperature: -5 °C to +45 °C