catalogue.gira.com

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

eNet wireless energy sensor, 4-gang

GIRA Data sheet



Specifica	ation	Order No.	Packing unit	£/piece without VAT	PS	EAN
	DRA	5473 00	1	274.78	42	4010337774372

Features

- The eNet radio energy sensors enable the radio transmission of voltage, electricity, and energy values to the eNet server.
- Logging electricity and voltage of the connected device.
- Calculation of effective output, reactive power, apparent power, and active electrical energy.
- Event- or time-controlled transmission of measurement value telegrams to the eNet server.
- Time synchronisation using the eNet server.

Technical data

Rated voltage: AC 230 V, 50/60 Hz

-5 °C to +45 °C Ambient temperature:

Measurement range

- Electricity: 0 mA to 16 A 0 to 3680 W - Electrical power: - Energy consumption: 0 to 99999 kWh

Wireless frequency: 868.3 MHz

Range (free field): approx. 100 m

Rated load current: 16 A

Max. 4 mm² Connection cross section:

Length of the data line: Max. 3 m

GIRA Data sheet

catalogue.gira.com

© Copyright by Gira Giersiepen GmbH & Co. KG All rights reserved

www.gira.com

Notes							
- An eNet server is required to operate this DIN rail adapter.							
Dimensions							
Modular width (MW):	4						